

## A PRODUCT FEATURES:

- Bluetooth v2.0
- Specifically design for Apple iPad
- Also works with Mac, PC, and various smartphones
- Scissor-switch keypad design, comfortable and ergonomic design
- Built-in intelligent power manage software for power conservation
- Power by build-in lithium-ion rechargeable battery
- Rechargeable battery gives over 300 hours from a single charge

## B SPECIFICATIONS

- Frequency band: 2.4 - 2.4835GHz unlicensed ISM band
- Receiving sensitivity: -75dbm (standard)
- Battery Volume: 310mAh
- Working range: 10m
- Working Current: >4mA
- Standby current: >1mA
- Charging time: 3-4 hours
- RF output power: up to 4dbm as maximum, good for your health with lowest radiates
- Operation distance: 0 - 10 m
- Dimension: 220\*120\*7.5(5.5)mm
- Net weight: 205g

## C SYSTEM REQUIREMENTS:

Mac iOS (i.e. iPad, iPhone)

## D INSTALLING BLUETOOTH KEYBOARD FOR IPAD (IOS)

1. Push the power button to "ON", and press "PAIRING" button. The blue light is flashing, now the keyboard is in pairing mode.
2. On your iPad / iPhone, select "settings"—"General".
3. Turn "Bluetooth" on, it will start searching for bluetooth devices.
4. Once your device finds the keyboard, select "HiPPIH Expression US" from the list.
5. Your device will now give you a 6 or 4 digit passkey. Enter this key onto the keyboard, and press Enter to complete the pairing(also on the keyboard).
6. The keyboard is now connected.



## **E** CHARGING

When the keyboard is low on power, the power indicator light will start flashing as red. It is recommended that you charge the keyboard at this time.

Charge as follows:

Using the charging cord, plug the Mini USB connector into the keyboard and the standard USB connector into an electrical power adapter or computer.

When charging, the red indicator light appears. When the battery has a full charge, the red light turns off. (Theoretical charging time is 3-4 hours)

## **F** STORAGE

After you are finished using the keyboard or while transporting the keyboard, switch the power to the OFF position. Turning off the keyboard's power will extend its battery life.

If you are going to store your keyboard for a long period of time, charge the keyboard for about half an hour before storing the keyboard. This will extend the life of the lithium-ion battery.

## **G** CARE

- Keep the keyboard away from sharp objects
- Do not force, stretch, distort, bend or fold the keyboard in any way
- Do not place heavy objects on top of the keyboard
- Keep keyboard away from microwave ovens
- Keep keyboard away from oil or organic liquids
- Do not immerse in water or pour water onto open areas or seams of keyboard



# KEYBOARD FOLIO INSTALLATION INSTRUCTIONS

Instructions For Setting Up Your Bluetooth Keyboard